

Insel Rectifiers (India) Pvt. Ltd.

151, 152 Udyog Kendra Extn II, Ecotech III
Greater Noida: 201306, U.P., India

☎ 1800 3070 9989 ✉ insel@rectifierindia.com

🌐 www.rectifierindia.com

1 - ϕ BRIDGE RECTIFIER MB 35




FEATURES

- 👉 Reverse voltage upto 1600V
- 👉 Epoxy insulated

TYPICAL APPLICATIONS

- 👉 Internal power supplies for electronic equipments
- 👉 DC Power supplies

**1 - ϕ BRIDGE
RECTIFIER
MB 35**



TECHNICAL DATA

DEVICE TYPE

V_{RRM}
(V)

V_{RSM}
(V)

MB35-10	1000	1100
MB35-12	1200	1300
MB35-16	1600	1700

SYMBOL	CONDITION	VALUES
I_{DC}	$T_{case} = 85^{\circ}C$	35 amp.
I_{FSM} I^2_t	$T_{vj}=130^{\circ}C$ $T_{vj}=130^{\circ}C$	370 amp. 680 A ² S
I_{RRM}	$T_{vj}=25^{\circ}C$ $T_{vj}=130^{\circ}C$	1.0mA 5.0mA
V_F	$T_{vj}=25^{\circ}C$ ($I_F=35$ Amp.); max	1.17 V
V_o R_o	$T_{vj}=25^{\circ}C$ ($I_F=25$ Amp.); max	0.85 V 5 mA
$R_{th(j-c)}$ T_{vj} T_{stg}		1.2 $^{\circ}C/W$ 125 $^{\circ}C$ 125 $^{\circ}C$
Mounting torque		2.5 Nm
Weight	Approx.	20 gm
V_{isol}	A.C. 50hz r.m.s Duration 1 min	2500 V
Package Outline		IR-10,IR-11,IR-12,IR-13

1 - ϕ BRIDGE RECTIFIER MB 35





FIG. 1 typical forward current derating curve

FIG. 2 maximum non-repetitive peak forward surge current





FIG. 3 typical instantaneous forward characteristics

1- ϕ BRIDGE RECTIFIER MB 35








FIG. 4 typical reverse characteristics

FIG. 5 typical junction capacitance



IR-10





IR-11

**1 - ϕ BRIDGE
RECTIFIER
MB 35**



PACKAGE OUTLINE



all dimensions in mm